



AVR-X250BT

5.1CH AV SURROUND RECEIVER WITH BLUETOOTH

THE PERFECT SOLUTION FOR HOME CINEMA STARTERS.

Representing the perfect combination of high performance and high value, the Denon AVR-X250BT delivers superb sonic fidelity along with a host of advanced features including full 4K compatibility, HDR (High Dynamic Range), and ARC (Audio Return Channel) for the complete home cinema experience.

HIGHLIGHTS

- 5.1 channel AV Receiver with 130W per channel
- 4K/60 Hz full-rate pass-through, HDR, ARC and HDMI CEC
- 5 HDMI inputs with full HDCP 2.2 support (on 3 inputs)
- Bluetooth Music Streaming
- Dolby TrueHD and DTS-HD Master Audio
- Setup Assistant
- Intelligent ECO mode

YOUR BENEFITS

- Enough power to fill your room with unique Denon sound
- Future-proof standards and convenient one-cable HDMI connection to TV
- Plenty of inputs for your Blu-ray Player, game console and more
- Conveniently play songs directly from your smartphone or tablet
- Blockbusting sound with high resolution audio formats
- Hassle-free installation and setup
- Energy-conscious without compromising on performance



Powerful 5 channel Discrete Amplifier

Featuring high current discrete power output devices on all channels, the AVR-X250BT delivers high power and is rated at a maximum of 130 watts per channel. There's also an Auto Eco mode that adjusts the maximum power available according to the volume level. For compatibility with the widest range of loudspeakers the AVR-X250BT is equipped with low impedance drive capability that provides operational stability with 6 ohm speakers.

Advanced HDMI Video Section

Featuring 5 HDMI inputs, the AVR-X250BT's video section features all you need for the full home cinema experience: Full 4K Ultra HD, HDCP 2.2, HDR (High Dymanic Range), BT.2020, Wide Color Gamut, 4:4:4 Pure Color sub-sampling, as well as 21:9 and 3D video pass-through.

Built-in Bluetooth

Thanks to built-in Bluetooth, you can easily stream your music from any compatible Bluetooth phone, tablet or computer. Simply select the AVR-X250BT from your device's Bluetooth menu to turn on the receiver and start playing your music. The AVR can remember up to 8 paired Bluetooth devices, so family and friends can listen to their favourite tracks.

Easy To Setup

For ease of setup, the AVR-X250BT has colour-coded loudspeaker terminals, and comes with colour-coded speaker labels that help ensure correct speaker cable hookups the very first time. With our exclusive Setup Assistant along with the Quick Start Guide, you can connect and configure your home cinema system quickly and easily. The Setup Assistant features clear on-screen text that quickly and easily guide you through the setup process, optimizing critical system settings for the best possible sound quality.

Easy To Use

The AVR's front panel features 4 Quick Select function buttons so you can quickly choose from the most popular sources and the system remembers your preferred audio settings for each one. The ergonomic remote control also features dedicated Quick Select buttons. And when you connect the AVR to your Smart TV you have the option of controlling the AVR via the TV's remote control which lets you select an input, adjust the volume and choose the surround sound mode.

Compatible with HEOS Link

Denon's HEOS wireless music streaming system delivers the ultimate in sound quality, ease-of-use and system flexibility. Sold separately, the HEOS Link enables the AVR-X250BT to play back nearly unlimited online music sources, like Internet Radio or popular music streaming services like Spotify, Deezer or TIDAL. Furthermore, once connected to the HEOS Link, the AVR-X250BT can easily be controlled via the free HEOS app.



Technical information		
Number of power amps	5 (Front L/R, Center, Surround L/R)	FM section
Power output	130 watts per channel (6 ohms, 1 kHz, THD 1%, 1ch driven)	Tuning frequency range
	90 watts per channel (6 ohms, 1 kHz, THD 0.7%, 2ch driven)	AM section
	70 watts per channel (8 ohms, 20 Hz - 20 kHz, THD 0.08%, 2ch driven)	Tuning frequency range
Speaker impedance	4 - 16 ohms	General
Preamplifier section		Power supply
Input sensitivity/impedance	200 mV / 47 kohms	Power consumption
Frequency response	10 Hz - 100 kHz — +1, -3 dB (DIRECT mode)	No-Sound
S/N Ratio	98 dB (IHF-A weighted, DIRECT mode)	Dimensions (W x H x D)
		Weight

Ports		
IN	HDMI	x 5
	Composite (video)	x 2
	Analogue Audio	x 2
	Digital Optical	x 2
OUT	HDMI Monitor	x 1
	Composite Monitor	x 1
	Audio Preout (SW)	0.1 ch
	Phones	x 1
OTHER	FM Tuner Antenna	x 1
	AM Tuner Antenna	x 1

EAN	AVRX250BTBKE2	4951035065136	Black
UK	AVRX250BTBKE2GB	4951035066379	Black

Denon Europe
A Division of Sound United
Beemdstraat 11
5653 MA Eindhoven
The Netherlands
www.denon.eu

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. • DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. • The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses • Other trademarks and trade names are those of their respective owners.
Denon is a trademark or registered trademark of D&M Holdings, Inc.
* All specs can be subject to change * Available only in Black